
www.kondator.se

Axessline
Outlet Conference

■ 935-T7DD


1 DECIDE & POSITION POWER STRIP


Position the Axessline power strip on a compatible tray and align the holes of the power strip to the holes of the tray. Make sure it aligns on both sides.



2 FIXATE TRAY TO SURFACE

For this step, **2x** M6 nuts & **2x** M6x8 screws are needed to fixate the power strip to the compatible tray (See **C**). Be sure to fixate to a tray or surface before continuing to the next step.






Not included


3 CONNECT

Once the power strip is fixed to the tray, connect cables to corresponding external components.



Ext. cable not included


✪WIELAND (Female)



Ext. cable not included

WIELAND CONNECTION GUIDE

Male Diagram	Female Diagram
L ⏚ N	N ⏚ L
1 2 3	3 2 1



Ext. cable not included

*WIELAND (Male)

✪ **Note!** Daisy chained units (wiring of multiple devices using GST connections) maximum power consumption must under no circumstances exceed 3500 Watt.

C COMPATIBLE TRAYS

■	**429-FX05**	Cable Tray Expand 950-1800 mm, silver
□	**429-FX05W**	Cable Tray Expand 950-1800 mm, white
■	**429-FX05B**	Cable Tray Expand 950-1800 mm, black
■	**935-TK61**	Axessline PDU Tray 670 x 220 mm, silver
□	**935-TK61W**	Axessline PDU Tray 670 x 220 mm, white
■	**935-TK61B**	Axessline PDU Tray 670 x 220 mm, black
■	**429-4001**	Cable Tray 720 mm, silver
□	**429-4004**	Cable Tray 720 mm, white
■	**429-4002**	Cable Tray 720 mm, black



Accessories:

Wieland ↔ Schuko

935-BA20	2.0 m
935-BA30	3.0 m
935-BA50	5.0 m

WIELAND GST18I3S Female type
Part no 92.931.3053.1
VDE Approval no. 40018414
Cable cord specification
H05VV-F according to EN50525-2-11
minimum 3 x 1.5 mm

OR

Certified equivalent connector.

For indoor use only.
Temperatur: 5 - 45 °C
Humidity: 20 - 80% RH

IP code: 20

INPUT: 250V, 16A, 50Hz
OUTPUT: 250V, 16A, 50Hz (Grounded)
Max 3500W ✪

Kondator AB, Energivägen 8 - Box 121, SE-135 23 TYRESÖ, SWEDEN

Revised 190905